

NADY AX-1000

FM Radio Wireless Instrument Transmitter with Echo and Distortion Effects

The Ultimate Guitar Accessory

The Wireless AX-1000 is the newest addition to Nady Systems' road proven, award-winning family of wireless products. As the ultimate guitar practice tool, the Wireless AX-1000 allows private practice like guitar headphone units, but offers much more. Features include Nady's exclusive BigRoom™ switchable echo, adjustable TubeVoice™ distortion, and a wireless transmitter for transparent audio broadcast or high quality recording through an FM radio—all engineered into a professional quality Nady bodypack transmitter. The Wireless AX-1000 is perfect for either the beginner looking for a low-cost amplifier & effects alternative or the seasoned working musician needing a practice unit.

Easy to Use

Unlike traditional guitar systems, this wireless does not come with a receiver, and no additional amplifier is required. The Wireless AX-1000 bodypack transmitter can be easily used with any FM radio such as a boom box, car or pocket radio, personal stereo, or home sound system—with or without headphones. Guitarists of all styles can practice or play wireless anywhere with echo and distortion

effects that deliver full concert hall sound—even from a portable radio. Range is up to 100 feet.

Built-In Echo & Distortion for Custom Tone

The Nady Wireless AX-1000 offers wireless freedom, high quality sound, and the wide variety of tones that guitarists demand—from crisp clarity with bite to ultimate shred with sustain and depth. A cost-effective alternative to traditional practice set-ups, the AX-1000 can even be used for gigs or as a backup wireless anywhere an FM radio is available.

Compact and Portable

Powered by a 9V alkaline battery with up to 12 hours of battery life, the compact

Patent Pending

Wireless AX-1000 transmitter weighs less than 5 ounces, stores easily in a guitar case, and has a belt clip that attaches securely to any guitar strap, belt or pocket. The unit features 1/4" phone jack with guitar cable and transmits in a fixed frequency at the bottom of the FM broadcast band with no transmitter tuning required. Controls include a power off/on/echo switch, power on LED, and adjustable distortion dial with marked settings.

NADY AX-1000 SPECIFICATIONS

Input Impedance: 1 M ohm w/permanently attached guitar cord and 1/4" phone plug

Frequency Response: 100Hz-9 kHz ± 3dB

Modulation: FM ± 75 kHz

Operating Range: Up to 100 feet

Controls: OFF/ON/ECHO switch, OFF/DISTORTION dial

RF Power Out: 150 µV/M@3M (max. allowed by FCC)

Battery: 9V alkaline

Battery Life: Up to 12 hours

Weight: 4.7 oz. (132 g.)

Dimensions: 8.5 x 6.5 x 2.25 cm (3.35" H, 2.75" W, .75" D)

Operating Frequency: Unit is pre-tuned to operate on a clear channel at the lowest end of the FM dial. FCC approved under Part 15.



Nady Systems, Inc. • 6701 Shellmound Street, Emeryville, CA 94608 • 510/652-2411 • FAX: 510/652-5075 • www.nadywireless.com