

PRA-8 SPECIFICATIONS

AUDIO INPUTS & PRE AMPS

Connectors	XLR
Type	Balanced
Impedance	2k Ohms
Min Sensitivity	-40dB
Peak input level	+5dB
Gain control range	50dB
Peak amplification	74dB
Phantom power	+48V, switchable

AUDIO OUTPUTS

Connectors	1/4" jack
Type	TRS Balanced
Impedance	600 Ohms
Peak output level	+18.5dB

DISTORTION, FREQUENCY RESPONSE, S/N RATIO & CROSSTALK

Frequency response	20Hz~20kHz, 0dB~-2B
Distortion	0.02%
S/N Ratio	Better than 80dB
Crosstalk rejection	>70dB@1kHz; -20dB input

POWER SUPPLY

Power Requirements	selectable, ~ 100-120 VAC, ~ 200-240 VAC, 50-60 Hz
Fuse	100-120 VAC: 630 mA (slow-blow) 200-240 VAC: 315 mA (slow-blow) 100-240 VAC: 500 mA (slow-blow) 5X20mm glass type
Power cord connector	Standard IEC receptacle with built-in fuse holder

PHYSICAL

Dimensions	1.75"X 19"X 8.5" (44.5X482.6X217mm)
Weight	7.48lbs (3.4Kg)

The specifications above are correct at the time of printing of this manual. For improvement purposes, all specifications for this unit, including design and appearance, are subject to change without prior notice.